GS-TS-000024



How to Rename Bluetooth

Version 1.0

Jul - 22



Table of Contents

Copyright	3
Service Information	3
Revision History	3
Overview	4
Operation	4
Use APP to change Bluetooth name	4
Use barcode change Bluetooth name directly	17



Copyright

GENERALSCAN reserves the right to make changes to any product to improve reliability, function, or design.

GENERALSCAN does not assume any product liability arising out of, or in connection with, the application or use of any product, circuit, or application described herein.

Service Information

If there is a question with the barcode scanner, you can visit website for the live chat at: <u>www.generalscan.com</u>

Revision History

Version	Date	Description
1.0	Jul-22	Initial Release



Overview

This file is used to introduce how to use APP to change the Bluetooth name of scanner. If use 1D scanner, please print the barcode on the screen out and scan.

When use, please open the Bluetooth of device.

Operation

Use APP to change the Bluetooth name

Use Android phone to scan the 2D barcode to download.





Step1: Open software GService





Step2: Input the account number and password, if don't have account number, please send email to support@generalscan.cloud to apply from us.





Step3: Choose Rename

09:36 👁 🖬 🖬	≜ k. Ø
← GService	
Registration	Rename
	5
New Barcode	Scanner Config
\bigcirc	
Other	Online Support

Step4: Scan Bluetooth SPP Mode

09:36 👁 🖼 🕯	2	16 k. P
Rename		
Connect BT Rena) (ame Scan Bi	arcode Completed
tep1: Switch E 1D laser scanner r arcode in the Quic	Bluetooth S need scan Bl ck user guide	PP mode
Bleti	ooth SPP M	ode
Blet Step2: Connect Only 1D laser scar luetooth, other sc	Bluetooth anners need to anners can s	ode o connect kip this step
Blets Step2: Connect Only 1D laser scar luetooth, other sc	Bluetooth nners need to anners can s	ode o connect kip this step
Blet Step2: Connect I Only 1D laser scar luetooth, other sc Cc PREVIOUS	Bluetooth Bluetooth anners need to anners can s	ode o connect kip this step se



If use 1D scanner, please click Connect Device.



Choose the device that need to connect

	13:38 🖬 👁 🖬 🔹		S al 🕯	
\leftarrow	Select device			
Turn c	on bluetooth		TURNED ON	
Blueto	oth Pair PIN: 1234			
PAIRE	D DEVICES			
AVAIL	ABLE DEVICES			
*	EDIFIER BLE FC:E8:00:4D:37:C6			
*	GS-BarcodeScanner	_		
*	GS R1120-B12882 18:93:D7:6E:69:8B			
		_		
	Stop	Scan	C)
	111 0	C	<	

GENERALSCAN

Step5: Input password, click OK, complete pairing, the blue indicator light of scanner goes out.





Step6: Can custom Bluetooth name.

e.g.

segment1: gs

Segment2: r5000

Segment3: 001

The created Bluetooth name at last is gs-r5000-001

	0	09:37 🗢 🖬 👘 👘 👘 👘						(a	
÷	← Rename								
c		BT	Rena) ime	Scan) Barcod	e Co	- 🔘 omplete	юd
Plea	ase e	nter	blue	tooth	n nan	ne			-
Se	gment	: 1 g	s					(С
Se	gment	2 r5	5000					(С
Se	gment	3 0	01						С
Ful	l Nam	e g	s-r50	00-00	1				
*Tap the i	the g	reen	circle	on th	e righ	t of te	ext bo	x to s	ave
P	REVIO	JS		EXPOR	T PDF			NEXT	
)		0_		÷		÷	Er	nglish	
1	2	3	4	5	6	7	8	9	0
	@	#	\$	%		&		()
				?	/			+	×
۵	Ļ	?		1	23!#()				Ļ
				C)		\sim		

GENERALSCAN

Step7: Choose the green circle behind the filling information, lock information, when you input next time, no need to input this information any more.

	09:37 «	•	2				Tr d	(A
÷	Renan	ne						
Connec	t BT	Rena) ime	Scan) Barcod	e Co	- 🔘 omplete	юd
Please	enter	blue	tooth	n nan	ne			
Segme	nt 1 gs							۲
Segme	nt 2 r5	000						۲
Segme	nt 3 00	01						•
Full Na	me ga	s-r50	00-00	1				
*Tap the the input	green (circle	on th	e righ	t of t	ext bo	ox to s	ave
PREVI	OUS		EXPOR	RT PDF			NEXT	
I	0_		÷		÷	Er	nglish	
1 2	3	4	5	6	7	8	9	0
!@	#	\$	%		&		()
			?	/			+	×
\$ \$?		1	23!0()	_			Ļ

After the green circle is chosen, when you finish naming the Bluetooth and give name to the next product's Bluetooth, the serial number of segment3 will change to 002, it means Bluetooth name will change to gs-r500-002



We also offer a method for giving name in bulk.

Choose EXPORT PDF

09:37	•	Se al â
← Ren	ame	
Connect PT	Danama Cara Danad	
Please ente	ar bluetooth name	e Completed
Segment 1		
Segment	ys.	C
Segment 2	r5000	\checkmark
Segment 3	001	\checkmark
Full Name	gs-r5000-001	
*Tap the gree	n circle on the right of t	ext box to save
the input		
PREVIOUS	EXPORT PDF	NEXT
111	0	<



Fill the table, fill as the below example, it means create barcode about the Bluetooth name from gs-r5000-01 to gs-r5000-099 these 99 Bluetooth names.

Barcode Height: 25mm

Page Size: A4

09:3	7 👁 🖬 🖬		S. al â					
← exp	← EXPORT PDF							
Segment 1	gs							
Segment 2	r5000							
From Seq	001							
To Seq	099							
Barcode Height	25							
Page Size	A4		•					
PREV	PAGE		EXPORT					
11	L	0	<					



Click EXPORT, can save the created barcode PDF. Following the path can find the PDF file, scan directly or print out to scan.



Also can open the file to check directly.

← EXF	PORT PDF		
			÷
Open wi	th		
		8	<u>&</u>
保存到钉钉云 盘	Google PDF Viewer	保存到网盘	网盘查看文档
Jus	tonce	Alwa	ays
11)	<



Created PDF file





Step8: Click NEXT

09:3	800 B	5.44
← Ren	ame	
Connect BT	Rename Scan Barcode Com	epieted
Please ent	er bluetooth name	
Segment 1	gs	۲
Segment 2	r5000	۲
Segment 3	001	0
Full Name	gs-r5000-001	
*Tap the greater the input	en circle on the right of text box	to save
PREVIOUS	EXPORT POF	EXT
	I 0 <	



Step9: Scan barcode, and click NEXT.

09.38 ← Rena	⇔ B ⊑ me		5.44
Connect BT	Rename	Scen Barcode C	🛞 ompletted
		gs-r5000-001 Scan the above barcode to rename, tap on the barcode to change barcode format.	
PREVIO	16	NEX	т
111	0) (

Step10: Scan barcode, Click NEXT DEVICE to operate the next product



Use barcode to change Bluetooth name directly

This is the URL link to generate the barcode

https://www.generalscan.net:8443/H5/CustomBarcode/

Step1: Scan the barcode below to change the Bluetooth name

Universal change Bluetooth name barcode

G1070: the order of change Bluetooth name

GS001: the name of Bluetooth after changing



If the product is R112X、R152X、R352X、R552X series, scan the barcode below, change the Bluetooth name to the format of product's model and product's SN.

If the product is R1521, SN is 123456, so after scanning, the Bluetooth name will change to GS R1521-123456

G1072: the order of change Bluetooth name

GS R1521: the name of Bluetooth after changing, on the end of this there will replenish "-123456" automatically, 123456 is the product's SN.







Default Factory Setting